



IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Application of:
Paulus Thomas Maria VAN ZEIJL

Serial No.: 09/730,452

Filed: December 5, 2000

Entitled: RECEIVER CIRCUIT

Art Unit: 2622

Examiner: Unknown

RECEIVED
JUL 12 2001
Technology Center 2600

Assistant Commissioner for Patents
Washington, D.C. 20231

CERTIFICATE OF MAILING BY EXPRESS MAIL

"EXPRESS MAIL" Mailing Label No. EL588405165US

Date of Deposit: 19 March 2001
I hereby certify that this paper or fee is being deposited with the U.S. Postal Service "Express Mail Post Office to Addressee" service under 37 CFR 1.10 on the date indicated above and is addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231

Type or Print Name: Jennifer Preuss

Signature: Jennifer Preuss

Dear Sir:

CLAIM OF PRIORITY UNDER 35 U.S.C. § 119

Under the provisions of 35 U.S.C. 119 Applicant hereby claims the priority of United Kingdom patent application No. 9929182.5 filed on December 9, 1999, which is mentioned in the declaration of the above-identified application. A certified copy of the priority document is filed herewith.

Respectfully submitted,

Robert W. Mason

Robert W. Mason
Reg. No. 42,848

Submitted: March 14, 2001
JENKENS & GILCHRIST, P.C.
1445 Ross Avenue, Suite 3200
Dallas, Texas 75202-2799
Telephone: 214-855-4196
Facsimile: 214-855-4300
Enclosures

This Page Blank (uspto)



INVESTOR IN PEOPLE

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

Technology Center 2600

JUL 12 2001

RECEIVED


I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

I also certify that the attached copy of the request for grant of a Patent (Form 1/77) bears an amendment, effected by this office, following a request by the applicant and agreed to by the Comptroller-General.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.




Signed

Dated 21 November 2000

CERTIFIED COPY OF
PRIORITY DOCUMENT

This Page Blank (uspto)



The
Patent
Office

1/77

10DEC99 E498288-4 002847
P01/7700 0.00-9929182.5

The Patent Office

Cardiff Road
Newport
Gwent NP9 1RH

Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

09 DEC 1999

1. Your reference

HL73281/000/SR

2. Patent application number

(The Patent Office will fill in this part)

9929182.5

3. Full name, address and postcode of the or of each applicant (underline all surnames)

TELEFONAKTIEBOLAGET L M ERICSSON

~~S-125 25~~ S-126 25
Stockholm
SWEDEN

ALL 24/12/99
leeb

Patents ADP number (if you know it)

If the applicant is a corporate body, give the country/state of its incorporation

SWEDEN

ENTERED IN THE
763730002

4. Title of the invention

RECEIVER CIRCUIT

5. Full name of your agent (if you have one)

Haseltine Lake & Co.

"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)

Imperial House
15-19 Kingsway
London WC2B 6UD

Patents ADP number (if you know it)

34001

RECEIVED
JUL 1 2 2001
Technology Center 2600

6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number

Country

Priority application number
(if you know it)

Date of filing
(day/month/year)

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Date of filing
(day/month/year)

8. Is a statement of inventorship and of right to a grant of patent required in support of this request? (Answer "Yes" if:

YES

a) any applicant named in part 3 is not an inventor, or
b) there is an inventor who is not named as an applicant, or
c) any named applicant is a corporate body.
See note (d))

Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form -

Description 12

Claim(s) 11

Abstract -

Drawing(s) 6

10. If you are also filing any of the following, state how many against each item.

Priority documents -

Translations of priority documents -

Statement of inventorship and right to a grant of patent (*Patents Form 7/77*) -

Request for preliminary examination and search (*Patents Form 9/77*) 1

Request for substantive examination (*Patents Form 10/77*) -

Any other documents (please specify) -

11. I/We request the grant of a patent on the basis of this application

Signature
Haroldine Lake

Date
8 December 1999

12. Name and daytime telephone number of person to contact in the United Kingdom

Mr. S. J. L. Rees

[0117] 9103200

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered "Yes" Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.

RECEIVER CIRCUIT

Field of the invention

5 The invention relates to an image reject circuit and to a method of rejecting images.

Background of the invention

Transceivers utilise frequency mixers for converting high frequency signals to low frequency
10 signals or vice versa. Such conversion is required, for example, to convert a signal from a desired frequency to an intermediate frequency (IF), an intermediate frequency (IF) being the difference between an incoming carrier frequency and a local-
15 oscillator (LO) frequency.

When converting frequencies in this manner an undesired image frequency is generated, and consequently, various methods have been developed to effectively eliminate the image signal.

20 Until recently, off-chip filters have been used to provide image rejection. However, the physical size of the components involved means that such circuits are not suited for implementation on an integrated circuit.

An alternative approach to filtering the image
25 signal is to cancel the image signal. Image cancellation or rejection mixers consist, for example, of two mixers, driven by two local-oscillator signals which have a 90° phase difference, and an IF phase shifter such that the two IF signals are again phase
30 shifted (usually 45° in one branch and 135° in the second branch) and a combiner or summing circuit. The result is that when the signals are summed, the desired signal components are added together while the undesired image signal components are cancelled,
35 resulting in a receiver having image rejection.

Image rejection circuits such as these rely on the accurate values of components. However, nominally identical components vary due to temperature variations, process spread and/or ageing and, as a consequence, calibration is therefore required during manufacture. For example, this can involve taking measurements during the manufacturing stage, and adjusting programmable resistors and/or capacitors accordingly.

As well as adding to the manufacturing process, once programmed the circuits are fixed, and cannot adapt to changes which may occur during use or ageing.

Another known method of improving image rejection is to use an inaccurate 90° phase shifter in the local oscillator path, which is corrected by an RC-polyphase correction network. However, to obtain an image rejection of about 50-60dB using this type of solution, the components within the respective devices must be matched to within 0.1%. Since mismatch usually scales inversely with silicon area, a large silicon area is therefore required to obtain an acceptable image rejection. A large silicon area implies large parasitic capacitances to the substrate, which in turn compromises high frequency performance. Also, the integrated circuit layout is very critical, as any parasitic capacitance or resistance degrades image rejection.

In addition to the disadvantages mentioned above, improving image rejection in the IF path will have limited effect unless corresponding steps are taken to improve image rejection in the LO path.

Known circuits for realising phase-shifters are shown in Figures 1 and 2 respectively, in which Figure 1 uses an all-pass phase shifter and Figure 2 uses a high-pass/low-pass phase shifter. Further known

solutions use inductors to realise the phase shifter in the LO path. However, inductors are large and thus not suited for implementation in an integrated circuit, (since two inductors of approximately $300\mu\text{m} \times 300\mu\text{m}$ are required).

Figure 1 shows a conventional all-pass phase shifter in which the input signal is connected to terminals 1, 3 which are connected across a bridge formed by resistors 5, 7 and capacitors 9, 11. Input signal 1 is connected to the junction of resistor 5 with capacitor 11, while the input signal 3 is connected to the junction of resistor 7 with capacitor 9. The balanced output signal 13 and signal 15 are taken respectively from the junction of resistor 7 with capacitor 11, and the junction of resistor 5 with capacitor 9. The output signals 13, 15 are phase shifted relative to the input signals 1, 3 by an amount determined by the values of the resistors and capacitors.

A first part of Figure 1 with $R=600\Omega$ and $C=1\text{pF}$, ($f=100\text{ MHz}$), gives a balanced I signal with, phase shifted by 45° from the input signal, while a second part with $R=3840\Omega$ and $C=1\text{pF}$, ($f=100\text{ MHz}$), gives the Q signal, phase shifted by 135° from the input signal. The phase difference between the I and Q signals is then 90° .

Ideally, the all-pass phase shifter described above should have a flat amplitude response over all frequencies. However, the impedance levels of the I and Q branches are significantly different, which makes realisation of the flat amplitude difficult in practice. The phase shift equals $2 \cdot \arctan(\omega RC)$, and is usually made 45° in the I branch and 135° in the Q branch. The phase shift is only optimal at one frequency. Thus, this all-pass phase shifter does not

give sufficient performance for obtaining an image rejection of 40dB or more, and a wide bandwidth, in the presence of process spread (for example from wafer to wafer), and mismatch (for example between components on the same wafer).

As mentioned above, Figure 2 shows another known phase shifter for the LO path, and relates to a high-pass/low-pass phase shifter. Basically, this phase shifter comprises two all-pass phase shifters of Figure 1 connected together as shown, using a second bridge consisting of resistors 17, 19 and capacitors 21, 23 connected to the first bridge. The input signal 1 is connected to the junction resistor 5 with capacitor 11, while the input signal 3 is connected to the junction of resistor 19 with capacitor 21. Unlike Figure 1, the high-pass/low-pass phase shifter has a correct phase shift of 90° over all frequencies. This phase shifter has the advantage that the impedance in the I and Q branches are the same. The amplitude, however, will vary with frequency. Limiters are commonly used to lower the amplitude errors, but exhibit amplitude-to-phase conversions, thus generating phase errors from the amplitude errors. For this reason, the use of high-pass/low-pass phase shifters does not allow the mixing circuits to fulfill the requirement of image rejection.

The aim of the present invention is to provide an image rejection circuit which overcomes the disadvantages mentioned above.

Summary of the invention

According to a first aspect of the present invention, there is provided an image reject circuit comprising:

a local oscillator for producing a local

oscillator signal;

a tunable phase shifting network for receiving the local oscillator signal and producing an output in-phase (I) signal and an output quadrature (Q) signal;

5 a first amplitude detector for determining the amplitude of the output I signal;

a second amplitude detector for determining the amplitude of the output Q signal; and,

10 means for determining the difference between the amplitudes of the output I and Q signals, to produce a tuning signal for tuning the phase shifting network to bring the difference between the amplitudes of the output I and Q signals towards a desired level.

15 According to another aspect of the present invention, there is provided a method of rejecting an image signal, the method comprising the steps of a local oscillator for producing a local oscillator signal, and a tunable phase shifting network for receiving the local oscillator signal and producing an
20 output in-phase (I) signal and an output quadrature (Q) signal, the method comprising the steps of;

determining the amplitude of the output I signal;
determining the amplitude of the output Q signal;
determining the difference between the amplitudes
25 of the output I and Q signals, to produce a tuning signal; and,

using the tuning signal to tune the phase shifting network to bring the difference between the amplitudes of the output I and Q signals towards a desired level.

30 According to another aspect of the present invention, there is provided a tunable phase shifting network for use in an image reject circuit, the tunable phase shifting network comprising:

35 first and second input terminals for receiving an input signal;

a first phase shifting circuit connected between the first input terminal and a voltage reference;

5 a second phase shifting circuit connected between the voltage reference and the second input terminal;

wherein each phase shifting circuit comprises:

10 first and second parallel arms connected between the respective input terminal and the voltage reference;

the first arm comprising a resistive element connected in series with a capacitive element;

15 the second arm comprising a capacitive element connected in series with a resistive element; and,

I and Q output lines being connected to respective junctions between the series connected resistive element and capacitive element; and,

20 wherein the phase shifting network further comprises a tuning input for receiving a tuning signal for adjusting an RC time constant of the phase shifting network.

25 Brief Description of the drawings

For a better understanding of the present invention, and to show more clearly how it may be carried into effect, reference will now be made, by way of example, to the accompanying drawings, in which:-

30 Figure 1 shows a conventional all-pass phase shifter;

Figure 2 shows a conventional high-pass/low-pass phase shifter;

35 Figure 3 shows an image rejection circuit according to a first aspect of the present invention;

Figure 4 shows a tunable high-pass/low-pass phase shifter for use in Figure 3, according to a second aspect of the present invention;

Figure 5 shows a known amplitude detector for use in Figure 3;

Figure 6 shows another known amplitude detector for use in Figure 3;

Figures 7a-7d show the response of an RC phase shifter according to the prior art; and,

Figures 8a-8d show the response of an RC phase shifter according to the preferred embodiment of the present invention.

Detailed description of a preferred embodiment of the present invention

Figure 3 shows a schematic diagram of an image rejection circuit according to the present invention. A voltage controlled oscillator 26 generates a LO signal, the frequency of which is dictated by circuit 24. The output of circuit 24 is connected to a voltage follower 28, which provides a balanced input signal 1, 3. Alternatively, in practice, items 24, 26 and 28 may be replaced by an oscillator/PLL circuit.

An RC tunable phase shifter 29 has first and second inputs for receiving the input signal 1, 3. It also receives a reference signal 31 which is connected, for example, to ground. The phase shifter 29 outputs complementary I and Q signals 13, 25 and 15, 27 respectively.

The I output signals 13, 25 are connected to a first peak or amplitude detector 33 which determines the amplitude of the I signal. The Q output signals 15, 27 are connected to a second peak or amplitude detector 35 which determines the amplitude of the Q signal. The outputs of the first and second peak

detectors 33 and 35 are compared in a comparator 37, which produces a difference signal, or tuning signal 39 based on the difference between the amplitudes of the I and Q signals. The tuning signal 39 is fed back to the "tune" input 41 of the RC phase shifter 29, and is used to tune the RC phase shifter as described below with reference to Figure 4.

Thus, in use, as the frequency of the input signal changes, say from 2.0 to 3.4 GHz, the amplitudes of the I and Q signals will change accordingly. The change in amplitudes is detected by each of the peak detectors 33, 35, thereby causing the tuning signal 39 to change. The tuning signal 39 is fed back to the RC phase shifter 29, which tunes the phase shifter such that the amplitudes of the I and Q signals become substantially equal once more, thereby maintaining optimum image rejection.

Figure 4 shows the tunable RC phase shifter of Figure 3 in greater detail, in accordance with a second aspect of the invention. The tunable RC phase shifter 29 is similar to the phase shifter of Figure 2 in that it basically comprises two all-pass phase shifters connected together. However, the capacitors 9, 11, 21 and 23 have respectively been replaced by junction diodes 43, 45, 47 and 49. The difference signal or tuning signal 39 is connected to opposite ends of the phase shifter via resistors 51 and 53. Preferably, capacitor 55, 57, 59, 61 are provided in series with each of the output terminals 13, 15, 25 and 27 respectively, for minimising of the interaction with the remaining circuitry.

The junction diodes 43, 45, 47, 49 function in a similar way to varactor diodes, such that varying the DC voltage across the diodes causes the capacitance of the diodes to be changed, thus enabling the phase

shifter to be tuned. The tuning signal 39 is the difference between the amplitudes of the I and Q signals, which has been fed back from the comparator 37 as described in Figure 3. Thus, the tunable RC phase shifter 29 can continually and automatically compensate for differences in amplitude between the I and Q signals which may have been caused by, for example, variation of components, or variation introduced by ageing or temperature fluctuations.

The embodiment described above tunes the phase shifter by varying the capacitance (i.e. by varying the voltage across the junction diodes 43, 45, 47 and 49). Alternatively, the phase shifter may be tuned by varying the resistance of the resistors 5, 7, 17 and 19, for example by operating a MOSFET in its triode region, such that it functions as a voltage dependent resistor. In such an embodiment, the gate of the MOSFET is connected to the tuning signal, and the drain and source are connected to the respective resistor connections.

Thus, the RC time constant may be changed by either varying the capacitance alone, varying the resistance alone, or varying a combination of the capacitance value and the resistance value.

Alternatively, either the resistive elements or the capacitive elements described above may be replaced by inductive elements, such that the time constant can be varied by changing the LC or RL time constants respectively.

Figure 5 shows a known peak detecting circuit for measuring the amplitude of the I and Q signals. The input signal is connected to the first terminal of a capacitor 63 via a series connected resistor 65 and forward polarity diode 67. The capacitor 63 stores the peak amplitude of the input signal, which is made

available at the output terminal. This type of circuit is particularly suited to high frequency applications.

Figure 6 shows an alternative circuit for determining the peak amplitude of the I and Q signals, and is also known in the art. The circuit of Figure 6 has the advantage of being more sensitive, and is capable of detecting smaller signals than that of Figure 5, (i.e. below the diode voltage drop). It is noted that the voltage controlled voltage source 69 may be replaced by an operational amplifier.

Although two alternative circuits for determining the peak amplitude have been shown in Figures 5 and 6, other circuits for measuring the peak amplitude may also be used without departing from the scope of the invention. For example, amplitude detectors using quadratic function circuits may be used.

Furthermore, any small residual errors still present in the amplitudes of the output signals may be corrected by adding a limiter stage to the RC phase shifter. Since only a small amplitude error is to be corrected, the limiter can have a limited gain or power consumption, thereby avoiding the disadvantages mentioned above in relation to limiter circuits.

Alternatively, any error residual errors may be removed by adding an RC poly-phase filter section, having a small Si-area, for example after the tunable phase shifter and before the following stages (i.e. mixer).

Although the embodiment described above uses the amplitude difference to tune the phase-shifter in the LO path, the tuning signal 39 may also be used to tune a phase shifter provided in the IF path.

Figure 7 shows the response of an open-loop simulation, ie. without the feedback circuitry of the present invention. As can be seen, as the frequency

changes from 2.0 to 3.4GHz in Figure 7a, the amplitude of the I and Q signals change accordingly, (as shown in Figures 7c and 7b respectively). Without any feedback to tune the RC phase shifter, the amplitudes of the I and Q signals remain different, as shown in Figure 7d, thereby reducing the effect of the image rejection circuitry.

Figure 8 shows the response of the preferred embodiment shown in Figure 3, in which the tuning signal from the comparison of the peak detectors is fed back to the RC phase shifter. As the frequency changes from 2.0 to 3.4 GHz, (as shown in Figure 8a), the amplitudes of the I and Q signals initially become different. However, this change is detected by the amplitude detectors, and used to tune the RC phase shifter such that the amplitudes of the I and Q signals become equal once more, as shown in Figure 8d.

According to the embodiment described above, the absolute accuracy of the amplitude detectors per se are not important, provided that the two amplitude detectors (one for the I branch and one for the Q branch) are matched. Similarly, the performance of the embodiment described above is not significantly degraded if the detection efficiency of the peak detectors is frequency dependent, as long as the two devices are matched.

Although the invention described above has been concerned with eliminating differences between the amplitudes of the output I and Q signals, the invention could equally be applied in situations where it is desired to introduce an amplitude difference to compensate for amplitude errors found elsewhere in the system, for example, to compensate for amplitude errors in the mixer conversion gains and/or in the IF-gain stages.

For example, in some systems, the gain of the I-mixer and the Q-mixer or an I_IF-phase shifter and a Q_IF-phase shifter are different. For example, when an all-pass phase shifter is used, the I_IF-phase shifter has a 45° phase shift ($R=600\Omega$, $C=1\text{pF}$, $f=100\text{ MHz}$) and the Q_IF-phase shifter uses $R=3840\Omega$, $C=1\text{pF}$, $f=100\text{ MHz}$. This gives different loading of the previous or following stages which in turn give gain differences between the I or Q path. Such differences may be corrected by purposely making the gain of the first and second peak detectors slightly different.

Alternatively, the subtracting circuit (37 in Figure 3) may be given a slightly different gain for the two inputs, i.e. 1:1.1 or 1:0.9 instead of 1:1.

The image reject circuitry described above may be implemented as an integrated circuit, for example using CMOS, BiCMOS, SiGe, or GaAs technology.

Various modifications which are obvious to those skilled in the art may be made without departing from the scope of the invention as defined by the appended claims. For example, resistors 51 and 53 of Figure 4 may be replaced by inductors, or a combination of inductors and resistors.

CLAIMS

1. An image reject circuit comprising:

a local oscillator for producing a local
oscillator signal;

a tunable phase shifting network for
receiving the local oscillator signal and
producing an output in-phase (I) signal and an
output quadrature (Q) signal;

a first amplitude detector for determining
the amplitude of the output I signal;

a second amplitude detector for determining
the amplitude of the output Q signal; and,

means for determining the difference between
the amplitudes of the output I and Q signals, to
produce a tuning signal for tuning the phase
shifting network to bring the difference between
the amplitudes of the output I and Q signals
towards a desired level.

2. An image reject circuit as claimed in claim
1, wherein the phase shifting network has first
and second input terminals for receiving the local
oscillator signal, and comprises:

a first phase shifting circuit connected
between the first input terminal and a voltage
reference;

a second phase shifting circuit connected
between the voltage reference and the second input
terminal;

first and second pairs of complementary
output lines connected to each of the first and
second phase shifting circuits; and,

a tuning input for receiving a tuning signal.

3. An image reject circuit as claimed in claim 2, wherein each of the first and second phase shifting circuits comprises a bridge circuit, each bridge circuit comprising:

5 first and second parallel arms connected between the respective input terminal and the voltage reference;

the first arm comprising a resistive element connected in series with a capacitive element;

10 the second arm comprising a capacitive element connected in series with a resistive element; and,

15 each I and Q output line being connected to a respective junction between the series connected resistive element and capacitive element.

4. An image reject circuit as claimed in any one of claims 1 to 3, wherein the phase shifting network is tuned by adjusting an RC time constant.

20

5. An image reject circuit as claimed in claim 4, wherein the capacitive element comprises a reverse polarity junction diode, which is tuned in accordance with the tuning signal.

25

6. An image reject circuit as claimed in claim 4, wherein the resistive element comprises a variable resistor, which is tuned in accordance with the tuning signal.

30

7. An image reject circuit as claimed in claim 4, wherein the resistive element comprises a variable resistor, the capacitive element comprises a reverse polarity junction diode, both of which are tuned in accordance with the tuning

35

signal.

8. An image reject circuit as claimed in claim 6 or 7, wherein the resistive element comprises a MOSFET operated in its triode region.

9. An image reject circuit as claimed in claim 2, wherein each of the first and second phase shifting circuits comprises a bridge circuit, each bridge circuit comprising:

first and second parallel arms connected between the respective input terminal and the voltage reference;

the first arm comprising a resistive element connected in series with an inductive element;

the second arm comprising an inductive element connected in series with a resistive element;

each I and Q output line being connected to a respective junction between the series connected resistive element and inductive element;

wherein the phase shifting network is tuned by adjusting the RL time constant.

10. An image reject circuit as claimed in claim 2, wherein each of the first and second phase shifting circuits comprises a bridge circuit, each bridge circuit comprising:

first and second parallel arms connected between the respective input terminal and the voltage reference;

the first arm comprising an inductive element connected in series with a capacitive element;

the second arm comprising a capacitive element connected in series with an inductive

element;

each I and Q output line being connected to a respective junction between the series connected inductive element and capacitive element;

5 wherein the phase shifting network is tuned by adjusting the LC time constant.

11. An image reject circuit as claimed in any one of claims 1 to 10, wherein the first and second
10 amplitude detectors comprise:

 an input terminal for receiving the input signal;

 a resistor and forward polarity diode connected between the input terminal and an output
15 terminal; and,

 a capacitor connected between the output terminal and ground.

12. An image reject circuit as claimed in any one of claims 1 to 10, wherein the first and second
20 amplitude detectors each comprise a two stage amplitude detector.

13. An image reject circuit as claimed in any one of claims 1 to 10, wherein the amplitude detectors
25 include a quadratic function circuit.

14. An image reject circuit as claimed in any one of the preceding claims, wherein the desired
30 difference between the amplitudes of the output I and Q signals is substantially zero.

15. An image reject circuit as claimed in claim 14, further comprising a limiting stage for
35 removing any residual difference between the

amplitudes of the I and Q signals.

16. An image reject circuit as claimed in claim 14 or 15, further comprising an RC poly-phase filter section for removing any residual difference between the amplitudes of the I and Q signals.

17. An image reject circuit as claimed in any one of claim 1 to 13, wherein the desired difference between the amplitudes of the output I and Q signals is set to a predetermined level, to compensate for an amplitude error found elsewhere in the system.

18. An image reject circuit as claimed in any one of the preceding claims, wherein the circuitry is implemented in bipolar technology.

19. An image reject mixer as claimed in any one of claims 1 to 17, wherein the circuitry is implemented in CMOS, BiCMOS, SiGe or GaAs technology.

20. An image reject circuit as claimed in any one of the preceding claims, wherein the circuit is implemented as an integrated circuit.

21. An image reject circuit as claimed in any preceding claim, further comprising a second tunable phase shifting network located in an intermediate frequency path, the tuning signal of the first phase shifting network also being used to tune the second phase shifting network.

22. A method of rejecting images in a receiver circuit comprising a local oscillator for producing a local oscillator signal, and a tunable phase shifting network for receiving the local oscillator signal and producing an output in-phase (I) signal and an output quadrature (Q) signal, the method comprising the steps of;

determining the amplitude of the output I signal;

determining the amplitude of the output Q signal;

determining the difference between the amplitudes of the output I and Q signals, to produce a tuning signal; and,

using the tuning signal to tune the phase shifting network to bring the difference between the amplitudes of the output I and Q signals towards a desired level.

23. A method as claimed in claim 22, wherein the phase shifting network is tuned by adjusting an RC time constant of the phase shifting network.

24. A method as claimed in claim 23, wherein the RC time constant is changed by changing the voltage across junction diodes, the change in voltage causing the capacitance of the junction diodes to change accordingly.

25. A method as claimed in claim 23, wherein the RC time constant is changed by changing the resistance value of a variable resistor

26. A method as claimed in claims 23, wherein the RC time constant is changed by changing the

capacitance value and the resistance value.

27. A method as claimed in claim 25 or 26,
wherein the resistance value is changed by
operating a MOSFET in its triode region.

28. A method as claimed in claim 22, wherein the
phase shifting network is tuned by adjusting an RL
time constant of the phase shifting network.

29. A method as claimed in claim 22, wherein the
phase shifting network is tuned by adjusting an LC
time constant of the phase shifting network.

30. A method as claimed in any one of claims 22
to 29, wherein the amplitudes of the I and Q
signals are determined using amplitude detectors.

31. A method as claimed in any one of claims 22
to 30, in which the receiver further comprises a
second tunable phase shifting network located in
an intermediate frequency path, the method
comprising the further step of tuning the second
phase shifting network according to the tuning
signal determined for the first phase shifting
network.

32. A method as claimed in any one of claims 22
to 31, wherein the phase shifting network is tuned
such that the desired difference between the
amplitudes of the I and Q signals is substantially
zero.

33. A method as claimed in any one of claims 22
to 32, wherein the phase shifting network is tuned

such that the desired difference between the amplitudes of the output I and Q signals is set to a predetermined level, to compensate for an amplitude error found elsewhere in the system.

5

34. A tunable phase shifting network for use in an image reject circuit, the tunable phase shifting network comprising:

10 first and second input terminals for receiving an input signal;

a first phase shifting circuit connected between the first input terminal and a voltage reference;

15 a second phase shifting circuit connected between the voltage reference and the second input terminal;

wherein each phase shifting circuit comprises:

20 first and second parallel arms connected between the respective input terminal and the voltage reference;

the first arm comprising a resistive element connected in series with a capacitive element;

25 the second arm comprising a capacitive element connected in series with a resistive element; and,

I and Q output lines being connected to respective junctions between the series connected resistive element and capacitive element; and,

30 wherein the phase shifting network further comprises a tuning input for receiving a tuning signal for adjusting an RC time constant of the phase shifting network.

35 35. A tunable phase shifting network as claimed

in claim 34, wherein the capacitive element comprises a reverse polarity junction diode, which is tuned in accordance with the tuning signal.

5 36. A tunable phase shifting network as claimed in claim 34, wherein the resistive element comprises a variable resistor, which is tuned in accordance with the tuning signal.

10 37. A tunable phase shifting network as claimed in claim 34, wherein the resistive element comprises a variable resistor, the capacitive element comprises a reverse polarity junction diode, both of which are tuned in accordance with the tuning signal.

15

38. A tunable phase shifting network as claimed in claim 36 or 37, wherein the resistive element comprises a MOSFET operated in its triode region.

20

39. A tunable phase shifting network for use in an image reject circuit, the tunable phase shifting network comprising:

25

first and second input terminals for receiving an input signal;

a first phase shifting circuit connected between the first input terminal and a voltage reference;

30

a second phase shifting circuit connected between the voltage reference and the second input terminal;

wherein each phase shifting circuit comprises:

35

first and second parallel arms connected between the respective input terminal and the

voltage reference;

the first arm comprising a resistive element connected in series with an inductive element;

5 the second arm comprising an inductive element connected in series with a resistive element; and,

I and Q output lines being connected to respective junctions between the series connected resistive element and inductive element; and,

10 wherein the phase shifting network further comprises a tuning input for receiving a tuning signal for adjusting an RL time constant of the phase shifting network.

15 40. A tunable phase shifting network for use in an image reject circuit, the tunable phase shifting network comprising:

first and second input terminals for receiving an input signal;

20 a first phase shifting circuit connected between the first input terminal and a voltage reference;

a second phase shifting circuit connected between the voltage reference and the second input terminal;

25 wherein each phase shifting circuit comprises:

first and second parallel arms connected between the respective input terminal and the voltage reference;

30 the first arm comprising an inductive element connected in series with a capacitive element;

the second arm comprising a capacitive element connected in series with an inductive element; and,

35

I and Q output lines being connected to respective junctions between the series connected inductive element and capacitive element; and,

5

wherein the phase shifting network further comprises a tuning input for receiving a tuning signal for adjusting an LC time constant of the phase shifting network.

This Page Blank (uspto)




Fig. 1




Fig. 2

This Page Blank (uspto)




Fig. 3

This Page Blank (uspto)




Fig. 4

This Page Blank (uspto)




FIG. 5




FIG. 6

This Page Blank (uspto)

OPEN-LOOP RESPONSE




FIG. 7

This Page Blank (uspto)

CLOSED-LOOP RESPONSE




FIG. 8

This Page Blank (uspto)